

# uPHP Reference

uPHP functions have an identical syntax to PHP functions in most cases. Below is a list of all the functions that have been implemented.

Certain additional functions are available as WattmonOS include files. For a list of these see [library\\_functions](#).

Click on the function name for further details:

FUNCTION NAME	PARAMETER(S)	RETURN	DESCRIPTION
<a href="#">adc_read</a>	int channel	int ADC value	Read an onboard ADC <a href="#">channel</a>
<a href="#">aes_decrypt</a>	string text, int length, string key, string iv	string with data	Return an AES-decrypted string
<a href="#">aes_encrypt</a>	string text, int length, string key, string iv	string with data	Return an AES-encrypted string
<a href="#">array</a>	mixed values ...	array	Create an <a href="#">array</a> , with optional <a href="#">values</a>
<a href="#">array_key</a>	array, int index	string key	Return the key for an <a href="#">array</a> index
<a href="#">array_keys</a>	array with key/value pairs	array of keys	Return keys for an <a href="#">array</a> that has key/value pairs
<a href="#">array_resize</a>	array indexed array, int length	none	Resize indexed <a href="#">array</a>
<a href="#">base64_decode</a>	string base64	string decoded or int 0	Decode a base64-encoded <a href="#">string</a>
<a href="#">base64_encode</a>	string to encode	string base64 or int 0	Return the base64-encoded version of a <a href="#">string</a>
<a href="#">call_user_func</a>	string function_name, mixed parameters ...	mixed result	Call a user defined function with optional <a href="#">parameters</a>
<a href="#">charat</a>	string, int index	int ASCII code	Return the ASCII code for a character in a <a href="#">string</a> at an <a href="#">index</a>
<a href="#">chdir</a>	string directory	int 0=OK	Change the current directory
<a href="#">chr</a>	int code	string 1 character	Return the character for an ASCII <a href="#">code</a>
<a href="#">clear_watchdog</a>			Clear the software watchdog timer
<a href="#">cos</a>	number radian_angle	float cosine	Return cosine of a <a href="#">radian_angle</a>
<a href="#">debug</a>	string output		Print to debug output
<a href="#">debugout</a>	int 0 or 1		Enable or disable debug messages
<a href="#">die</a>			Kill the script
<a href="#">disk_free_space</a>	int drive	int KiloBytes	Return free space on drive
<a href="#">disk_status</a>	int drive	int Status	Return mount status of drive
<a href="#">disk_total_space</a>	int drive	int KiloBytes	Return total space on drive
<a href="#">download</a>	string url	int res	Download a file in the background
<a href="#">download_info</a>		array info	Get info about ongoing download
<a href="#">download_state</a>		int status	Get state of download
<a href="#">error_reporting</a>	int verbosity		Set the debug output level
<a href="#">ereg</a>	string pattern, string content [, &array matches]	int	Perform a regex operation

FUNCTION NAME	PARAMETER(S)	RETURN	DESCRIPTION
exec	string script, int delay		Run a <a href="#">script</a> with an optional <a href="#">delay</a>
exec_action	mixed action	int 1=OK	Triggers a manually executable <a href="#">action</a> by id or name
explode	string, string delimiter	array	Turn a <a href="#">string</a> into an <a href="#">array</a>
f485open	int baud, int parity	int handle or 0	Open the RS-485 port at the specified <a href="#">baud</a> rate and <a href="#">parity</a>
fclose	int handle		Close a file, stream or socket
feof	int handle	int 1 or 0	Test if no more data is available in a file, stream or socket
fgets	int handle, int size	string or int -1	Return a single line from a file, stream or socket, with optional <a href="#">size</a> limit
file_exists	string filename	int 1 or 0	Check if a file exists
filesize	string filename or int handle	int bytes	Return the size of a file, or the number of unread bytes in a stream or socket
findfirst	string pattern, int attributes	array first file found	Start searching the current folder for files matching a <a href="#">pattern</a> and <a href="#">attributes</a>
findnext		array next file found	Return next matching file information (after a findfirst)
firmwareupdate			Initiate a firmware update sequence and reboot the device
floatval	mixed value	float value or int 0/1	Return the <a href="#">float</a> value of a <a href="#">number</a> or <a href="#">string</a>
flush	socket socket to flush		Flush current output or socket to the browser
fopen	string filename, string mode	int handle or 0	Open a file for reading or writing
fread	int handle, int bytes	string or int 0	Read <a href="#">bytes</a> from a file, stream or socket
fread_unpack	int handle, string format, int count, int interval	number	Write contents of an indexed array to a file in binary
freemem		int bytes	Return free memory space
freestack		int bytes	Return free stack space
fseek	int handle, int offset, int whence		Position the file pointer in an open file
fseropen	int baud, int blocking, int invert, int parity	int handle or 0	Open the serial port at the specified <a href="#">baud</a> rate with optional parameters
fsockopen	string host, int port, int timeout	int handle or 0	Open an internet socket connection with optional <a href="#">timeout</a>
ftell	int handle	int position	Return the current position of a file read/write pointer
ftp_command	string result	string command]	Send an FTP command
ftp_close	int result		Close an active connection with FTP server
ftp_download	int result	string remote_file, string local_file, [int position]	Initiate a download of a remote file

<a href="#">ftp_error</a>	<code>int result</code>		Get last FTP response code
<a href="#">ftp_is_busy</a>	<code>int result</code>		Check if the FTP engine is busy
<a href="#">ftp_is_connected</a>	<code>int result</code>		Check if the FTP connection is active
<a href="#">ftp_is_connecting</a>	<code>int result</code>		Check if the FTP connection is in the process of connecting
<a href="#">ftp_list</a>	<code>int result</code>	<code>string folder, string output_file</code>	Lists a folder on the FTP server and outputs the result to the specified file
<a href="#">ftp_open</a>	<code>int result</code>	<code>string host, int port, string username, string password</code>	Open a connection to an FTP server
<a href="#">ftp_size</a>	<code>int size</code>	<code>string filename</code>	Get the file size of a file on the FTP server
<a href="#">ftp_status</a>	<code>array status</code>		
<a href="#">ftp_upload</a>	<code>int result</code>	<code>string remote_file, string local_file, [int position]</code>	Initiate an upload of a file
<a href="#">function_exists</a>	<code>string function_name</code>	<code>int 1 or 0</code>	Check if a function exists (custom or native)
<a href="#">fwrite</a>	<code>int handle, mixed data, int length</code>	<code>int bytes written or -1</code>	Write <code>data</code> to a file, stream or socket
<a href="#">fwrite_pack</a>	<code>int handle, array data, int length</code>	<code>number</code>	Write contents of an indexed array to a file in binary
<a href="#">get3gstat</a>		<code>array</code>	Get cellular data connection status information
<a href="#">getcwd</a>		<code>string path</code>	Get the current directory
<a href="#">getethstat</a>		<code>array</code>	Get Ethernet connection status information
<a href="#">getmac</a>		<code>string MAC</code>	Get the Wattmon's MAC address
<a href="#">gettype</a>	<code>any variable</code>	<code>string type</code>	Get a variable type as a string
<a href="#">getusbstat</a>		<code>array</code>	Get USB host status information
<a href="#">getwifistat</a>		<code>array</code>	Get WIFI status information
<a href="#">header</a>	<code>string header_data</code>		Add to HTTP header
<a href="#">hash_hmac</a>	<code>string algorithm, string data, string key</code>	<code>string converted</code>	Generate a keyed hash value using the HMAC method
<a href="#">htmlspecialchars</a>	<code>string data</code>	<code>string converted</code>	Convert special characters for display in HTML
<a href="#">ieee754toint</a>	<code>float value</code>	<code>int representation</code>	Convert a <code>float value</code> to an IEEE-754 encoded <code>integer</code> (32 bit)
<a href="#">implode</a>	<code>array, string delimiter</code>	<code>string</code>	Turn an <code>array</code> into a <code>string</code>
<a href="#">include</a>	<code>string filename</code>		Include a file within the current script at the current location
<a href="#">indexed_array</a>	<code>int type, int size</code>	<code>array</code>	Create an <code>array</code> of a specific <code>type</code> and <code>size</code>

ini_get	string filename, string section, string key, mixed default	mixed value	Get a value from an INI file
ini_get_array	string filename, string section	array	Get a group of parameters from an INI file as an array
ini_put_array	string filename, array data, string section		Write a group of parameters to an INI file from an array
ini_set	string filename, string section, string key, mixed value	int 1=OK	Set a value in an INI file
init_watchdog	int interval		Initialize the software watchdog timer
inttoieee754	int representation	float value	Convert an IEEE-754 encoded integer representation (32 bit) to a float
intval	mixed value	int value	Return the integer value of a number or string
is_array	mixed variable	int 1 or 0	Check if a variable is an array
is_float	mixed variable	int 1 or 0	Check if a variable is a float
is_int	mixed variable	int 1 or 0	Check if a variable is an integer
is_numeric	mixed value	int 1 or 0	Check if a value is numeric (int, float or numeric string)
is_string	mixed variable	int 1 or 0	Check if a variable is a string
isset	mixed variable	int 1 or 0	Check if a variable exists
json_encode	array, int method	string	JSON encode an array into a string, with optional method
ln	number number	float log <sub>e</sub>	Return the natural logarithm of a number
log	string output, string file		Print to the System Log (or optional file)
log10	number number	float log <sub>10</sub>	Return the base 10 logarithm of a number
mail	string recipient, string subject, string body	int 0 or SMTP error code	Send an email [deprecated]
max_execution_time	int seconds		Set the maximum execution time for the current script
mb_add_dev	int id, int type, string name, int poll_interval, int status, int bus	int 0=OK	Add a device to the list of polled devices
mb_delete_dev	int id	int 1=OK	Delete a device from the list of active devices
mb_get_dev_by_id	int id	array	Return modbus device details by id
mb_get_dev_by_index	int index	array	Return modbus device details by index
mb_get_dev_by_name	string name	array	Return modbus device details by name
mb_get_dev_info	int type	array	Return modbus device details by type

mb_get_role_array		array	Return an array of all roles and their values
mb_get_status_by_role	int role	int 1=OK	Return status of the device attached to the role
mb_get_val_by_role	int role	number	Return value of the role
mb_num_devices		int	Return number of devices on the modbus
mb_queue_command	mixed values ...		Queue a sequence of characters to the RS-485 bus and get but ignore the reply
mb_scan_complete		int 1=complete, 0=ongoing	Check to see if a modbus scan has completed
mb_scan_percent		number percent completed	Return scan percentage completed
mb_send_command	mixed values ...		Send a sequence of characters to the RS-485 bus and get a reply
mb_set_dev_var	string name or int id, string variable, mixed value	int 1=OK	Set a variable on a modbus device
mb_set_val_by_role	int role, number value	int 1=OK	Set a role value on a modbus device
mb_start_scan	int start, int end		Initiate an automatic scan of the modbus
md5	string input	string 32 characters	Calculate the MD5 hash of a string
md5_file	string filename	string 32 characters	Calculate the MD5 hash of a file
mem_dump			Write the current memory map to /dump.txt
mem_usage			Write memory usage to standard output
microtime		int ms	Return the number of milliseconds since boot
mkdir	string pathname	int 0 or error code	Make a directory
mktimes	int hour, int minute, int second, int month, int day, int year	int seconds	Return the Linux Timestamp for a given date and time
mqtt_disconnect			Disconnect MQTT connection
mqtt_publish	string channel, string content	int 1 for success or 0 for error	Publish a message to an MQTT server
mqtt_subscribe	string channel, string callback	int 1 for success or 0 for error	Subscribe to a channel on an MQTT server
mqttstat	array array with connection status		Get MQTT Connection status
net_disable3g			Disable 3G support for the dongle
net_enable3g			Enable 3G support for the dongle
netstat	array		Get Ethernet information

number_format	<code>mixed number, int digits</code>	<code>string</code> formatted	Return the <code>string</code> value of a <code>number</code> formatted to a particular precision
nvram_backup	<code>string filename</code>	<code>int</code> bytes written or 0=error	Backup the contents of NVRAM to a file on the SD Card
nvram_defrag			Defragment NVRAM to optimise it
nvram_dump			Dump the contents of NVRAM to standard output
nvram_free		<code>int</code> bytes	Return the number of bytes available in NVRAM
nvram_get	<code>string key</code>	<code>mixed</code> value	Get a value from NVRAM
nvram_restore	<code>string filename</code>		Restore the contents of NVRAM from a file
nvram_set	<code>string key, string value</code>	<code>int</code> 1=OK	Set a <code>key</code> and <code>value</code> in NVRAM
nvram_unset	<code>string key</code>	<code>int</code> 1=OK	Clear a <code>key</code> from NVRAM
ord	<code>string character</code>	<code>int</code> ASCII code	Return the ASCII code for a <code>character</code>
ow_first		<code>array</code> or <code>int</code> 0	Initiate a OneWire bus scan and return the address of the first device found
ow_next		<code>array</code> or <code>int</code> 0	Return the address of the next OneWire device found (after an <code>ow_first</code> )
ow_read		<code>int</code> value or 0	Read a byte from the OneWire bus
ow_read_temp	<code>array device_id</code>	<code>float</code> degrees Celsius	Read a temperature from a device on the OneWire bus
ow_reset			Reset the OneWire bus
ow_write	<code>int value</code>		Write a byte to the OneWire bus
pack	<code>string format, mixed value</code>	<code>string</code>	Pack a value into a <code>string</code>
phpinfo		<code>string</code>	Return information about the system
pin_configure	<code>int pin_index, int pin_type, int counter_type</code>		Configure an I/O pin as a digital input, output, or analog input
pin_get	<code>int pin_index, int pin_type</code>	<code>int</code> value	Return the value of an I/O pin
pin_set	<code>int pin_index, int value</code>		Set a digital output to <code>value</code> 1 or 0
ping	<code>string host</code>	<code>array</code>	Send an ICMP ping and place the result in an <code>array</code>
power	<code>number base, number exp</code>	<code>number base<sup>exp</sup></code>	Return <code>base</code> raised to the power of <code>exp</code>
print	<code>string data</code>		Print <code>data</code> to the current output stream such as a web page or terminal
print_r	<code>array</code>		Dump the contents of an <code>array</code> to the current output

printf	string format, mixed values ...		Print a formatted string to standard output
process_kill	int pid		Send a kill request to a process
process_list		array	Return an array of the currently running scripts
rand	int min, int max	int	Return a random integer between min and max
reboot			Reboot the processor
register_callback	string callback_type, string filename, string functionname	int 0 or error code	Register a callback function for system events
rename	string source, string destination	int 0 or error code	Rename or move a file or directory from source to destination
reset			Reset the processor
rmdir	string pathname, int delete_contents	int 0=OK	Remove a directory, with optional deletion of contents
send_sms	string phone_number, string message	int result	sends an sms through a cellular dongle
session_destroy			Clear the current session's data
session_is_new		int	Check if a session was just initiated
session_start			Initiate a new session and send the cookie data for it
set_search_path	string pathname		Set the search path for the telnet client
setethpower	int state		Enable or disable the ethernet controller
setpriority	int priority		Set the priority of the current script
settime	int timestamp, int calibration		Set the system time from a Linux Timestamp, with optional calibration
setusbpower	int state		Enable or disable USB power
sha1	string input	string 40 characters	Calculate the SHA1 hash of a string
sin	number radian_angle	float sine	Return sine of a radian_angle
sizeof	array	int number of elements	Return the number of elements in an array
sleep	int ms		Sleep for specified milliseconds
snmp_trap_send	string message	int 0 or 1	Send an SNMP trap message with ASCII content of source
spi_clearcs			Clear the CS output of the SPI bus
spi_read		int byte	Read a byte from the SPI bus
spi_setcs			Set the CS output of the SPI bus
spi_write	int byte		Write a byte to the SPI bus
sprintf	string format, mixed values ...	string formatted	Return a formatted string
sqr	number number	number squared	Return the square of a number
sqrt	number number	number square root	Return the square root of a number
stats		array	Return system statistics

<a href="#">str_replace</a>	<code>string search, string replace, string subject</code>	<code>string result</code>	Return the string with each occurrence of <code>search</code> replaced with <code>replace</code>
<a href="#">strftime</a>	<code>string format, int timestamp</code>	<code>string formatted</code>	Format a Linux <code>Timestamp</code> using a <code>format string</code>
<a href="#">strlen</a>	<code>string input</code>	<code>int length</code>	Return the length of a <code>string</code>
<a href="#">strpos</a>	<code>string haystack, string needle</code>	<code>int position or -1</code>	Return the position of the first occurrence of a <code>needle</code> in a <code>haystack</code>
<a href="#"> strrpos</a>	<code>string haystack, string needle</code>	<code>int position or -1</code>	Return the position of the last occurrence of a <code>needle</code> in a <code>haystack</code>
<a href="#">strtolower</a>	<code>string input</code>	<code>string lowercase</code>	Return the lowercase version of a <code>string</code>
<a href="#">strtoupper</a>	<code>string input</code>	<code>string UPPERCASE</code>	Return the UPPERCASE version of a <code>string</code>
<a href="#">strval</a>	<code>mixed value</code>	<code>string</code>	Return the <code>string</code> equivalent of a <code>number</code>
<a href="#">substr</a>	<code>string input, int start, int length</code>	<code>string substring</code>	Return part of a <code>string</code>
<a href="#">tar_finish</a>	<code>int handle</code>	<code>int 1=OK</code>	Add the ending header to a TAR file
<a href="#">tar_put</a>	<code>int handle, string src.pathname, string tar.pathname</code>	<code>int 1=OK</code>	Add a file to an open file in TAR format
<a href="#">time</a>		<code>int seconds</code>	Return the current system timestamp
<a href="#">timefromfat</a>	<code>int filetime</code>	<code>int seconds</code>	Convert a FAT <code>filetime</code> to a Linux Timestamp
<a href="#">trim</a>	<code>string input</code>	<code>string trimmed</code>	Return the trimmed <code>string</code>
<a href="#">ucfirst</a>	<code>string input</code>	<code>string Lowercase</code>	Convert a <code>string</code> to Lowercase except for the first character
<a href="#">unlink</a>	<code>string filename</code>	<code>int 0 or error code</code>	Remove a file (delete it)
<a href="#">untar</a>	<code>string filename, int verbosity</code>	<code>int 1=OK</code>	Expand a TAR file into the current folder, optionally verbose
<a href="#">unpack</a>	<code>string format, string value</code>	<code>number</code>	Unpack a packed string value and return the original data
<a href="#">uptime</a>		<code>int ms</code>	Return the uptime in milliseconds
<a href="#">urldecode</a>	<code>string str</code>	<code>string string to encode</code>	URL-Decode a string
<a href="#">urlencode</a>	<code>string str</code>	<code>string encoded string</code>	URL-Encode a string
<a href="#">wifi_disable</a>			Disable Wifi module
<a href="#">wifi_enable</a>			Enable Wifi module

From:  
<http://wattmon.com/dokuwiki/> - **Wattmon Documentation Wiki**

Permanent link:  
<http://wattmon.com/dokuwiki/uphp/functions?rev=1626408047>

Last update: **2021/09/13 05:56**

