

# Modbus Library Reference

Available in Wattmon OS 3.12+

The Modbus include library contains functions and defines as shown below.

**Usage:**

```
include("/lib/uphp/modbus.inc"); [[modbus.inc|View Source]]
```

## Defines

DEFINE	VALUE
MB_ILLEGAL_FUNCTION	-1
MB_ILLEGAL_ADDRESS	-2
MB_ILLEGAL_VALUE	-3
MB_SLAVE_FAILURE	-4

## Functions

Click on the function name for further details:

FUNCTION NAME	PARAMETER(S)	RETURN	LIBRARY	DESCRIPTION
<a href="#">mb_get_error_string</a>	<a href="#">int</a> <a href="#">error</a>	<a href="#">string</a>	<a href="#">modbus</a>	Get human readable error description
<a href="#">mb_set_float_be_0x10</a>	<a href="#">int</a> <a href="#">id</a> , <a href="#">int</a> <a href="#">bus</a> , <a href="#">int</a> <a href="#">reg</a> , <a href="#">int</a> <a href="#">val</a> , <a href="#">int</a> <a href="#">retries</a>	<a href="#">int</a>	<a href="#">modbus</a>	Set a modbus float in big endian using function 10h
<a href="#">mb_set_float_le_0x10</a>	<a href="#">int</a> <a href="#">id</a> , <a href="#">int</a> <a href="#">bus</a> , <a href="#">int</a> <a href="#">reg</a> , <a href="#">int</a> <a href="#">val</a> , <a href="#">int</a> <a href="#">retries</a>	<a href="#">int</a>	<a href="#">modbus</a>	Set a modbus float in little endian using function 10h
<a href="#">mb_set_int16_0x03</a>	<a href="#">int</a> <a href="#">id</a> , <a href="#">int</a> <a href="#">bus</a> , <a href="#">int</a> <a href="#">reg</a> , <a href="#">int</a> <a href="#">val</a> , <a href="#">int</a> <a href="#">retries</a>	<a href="#">int</a>	<a href="#">modbus</a>	Set a modbus device register using function 03h
<a href="#">mb_set_int16_0x10</a>	<a href="#">int</a> <a href="#">id</a> , <a href="#">int</a> <a href="#">bus</a> , <a href="#">int</a> <a href="#">reg</a> , <a href="#">int</a> <a href="#">val</a> , <a href="#">int</a> <a href="#">retries</a>	<a href="#">int</a>	<a href="#">modbus</a>	Set a modbus device register using function 10h
<a href="#">mb_set_uint32_be_0x10</a>	<a href="#">int</a> <a href="#">id</a> , <a href="#">int</a> <a href="#">bus</a> , <a href="#">int</a> <a href="#">reg</a> , <a href="#">int</a> <a href="#">val</a> , <a href="#">int</a> <a href="#">retries</a>	<a href="#">int</a>	<a href="#">modbus</a>	Set a modbus UINT32 in big endian using function 10h
<a href="#">mb_set_uint32_le_0x10</a>	<a href="#">int</a> <a href="#">id</a> , <a href="#">int</a> <a href="#">bus</a> , <a href="#">int</a> <a href="#">reg</a> , <a href="#">int</a> <a href="#">val</a> , <a href="#">int</a> <a href="#">retries</a>	<a href="#">int</a>	<a href="#">modbus</a>	Set a modbus UINT32 in little endian using function 10h

## Example

```
<pre><?
// assume a modbus TCP connection on ID 1 on Channel 2
$DEBUG=1;

include("/lib/uphp/modbus.inc");
```

```
$id=1;
$bus=2;
$reg=1;
$cmd=100;
$retries=1;

$res=mb_set_int16_0x03($id, $bus, $reg, $cmd, $retries);
print("\r\nSet INT 16 func 03 result is : ".$res."
".mb_get_error_string($res));
$reg++;
$res=mb_set_int16_0x10($id, $bus, $reg, $cmd, $retries);
print("\r\nSet INT 16 func 10 result is : ".$res."
".mb_get_error_string($res));
$reg+=2;
$res=mb_set_uint32_le_0x10($id, $bus, $reg, $cmd, $retries);
print("\r\nmb_set_uint32_le_0x10 result is : ".$res."
".mb_get_error_string($res));
$reg+=2;
$res=mb_set_uint32_be_0x10($id, $bus, $reg, $cmd, $retries);
print("\r\nmb_set_uint32_be_0x10 result is : ".$res."
".mb_get_error_string($res));
$reg+=2;
$res=mb_set_float_le_0x10($id, $bus, $reg, $cmd, $retries);
print("\r\nmb_set_float_le_0x10 result is : ".$res."
".mb_get_error_string($res));
$reg+=2;
$res=mb_set_float_be_0x10($id, $bus, $reg, $cmd, $retries);
print("\r\nmb_set_float_be_0x10 result is : ".$res."
".mb_get_error_string($res));
?></pre>
```

From:

<http://wattmon.com/dokuwiki/> - **Wattmon Documentation Wiki**

Permanent link:

[http://wattmon.com/dokuwiki/uphp/library\\_functions/modbus?rev=1617959243](http://wattmon.com/dokuwiki/uphp/library_functions/modbus?rev=1617959243)

Last update: **2021/09/13 05:56**

