netstat

WMPRO, WMMINI FW >= 1.0 WMMEGA FW >= 2.0

Get Ethernet information

Description

array netstat ( )

This function returns an **array** containing information about the state of the network interface

Parameters

None

Return Values

Array containing the following keys and values:

KEY	TYPE	VALUE
max_http_connections	**int**	The number of HTTP connections allowed
max_connections	**int**	The total number of TCP connections allowed
internet_connected	**int**	Returns 1 if Internet is connected (only available in fw x.1203+)
interface	**int**	Returns 0 for Ethernet, 1 for Cellular, 2 for WiFi (only available in fw x.1203+)
conn**X**_socket[1)]	**int**	Socket number for connection X
conn**X**_stage	**int**	Socket status for connection X
conn**X**_info	**string**	Information about the connection if any. For connection info string details, see the sample below.
conn**X**_remote	**string**	Remote host IP address

Sample Connection Value

Open:0|Aborted:0|Process:0|Path:\app\|Fn:devcalib_ajax.cgi|Type:3|Time:0|Fstage:7|Context:0|Sockstate:4

Example

```
<?
  $arr=netstat();
  print("Total connections available: ".$arr['max_connections']);
```

```
?>
```

See Also

setusbpower() - Enable or disable USB power

net_enable3g() - Enable 3G support for the dongle

net_disable3g() - Disable 3G support for the dongle

getethstat() - Get Ethernet connection status information

1)
Zero-based connection number, up to max_connections-1

From:
http://wattmon.com/dokuwiki/ - **Wattmon Documentation Wiki**

Permanent link:
http://wattmon.com/dokuwiki/uphp/functions/netstat

Last update: **2021/12/10 09:18**